

ThingMagic® Sargas



87 mm L x 80 mm W x 24 mm H

Features & Benefits:

- Built Around Proven ThingMagic Technology
- User-friendly web interface included in software
- Broadest Range of Operating Temperatures for Both indoor and Sheltered Outdoor Environments
- ThingMagic Universal Reader Assistant and Mercury API Shortens Testing and Development Process
- Optional RAINstream to Allow Direct Transfer of Tag Data to Backend Systems Via Several Alternative Interface Protocols Eliminates Software Design

Applications:

- Cabinets and Lockers
- In-Vehicle, including Emergency Medical Services
- Mobile Asset Management
- Warehouse & Supply Chain
- Outdoor Sheltered Applications

2-Port UHF RAIN® RFID Reader

ThingMagic Sargas is a compact, high performance, multiprotocol, networked 2-port UHF RAIN RFID reader in a low profile enclosure with both read and write capability. With an onboard processor, memory and removable flash storage, it has features designed for enterprise applications as well as OEM system integration. Sargas is capable of reading more than 750 tags per second at distances over 9 meters when configured with appropriate antennas.

Powerful Processor

Sargas is outfitted with a powerful ARM Cortex processor running Linux and generous amounts of DDR and FLASH memory, allowing complex on-reader programs to be loaded and written with the aid of ThingMagic's MercuryAPI.

RAINstream Compatible

All settings, including those for RAINstream, can be configured via a web interface sourced by the reader. This interface also permits the administrator to view status, upgrade firmware, run diagnostic tests, and test reading ability.

"Tagnostic"

ThingMagic IZAR supports the entire suite of RAIN UHF RFID tag functionality, including Gen2V2 security. It also supports custom features from a wide variety of tag vendors, enhancing functionality for specialized applications. Optional, non-RAIN tag protocols are also available, including ISO 18000-6B, and read-only support for IP-X and AEI ATA.

Common Language

Mercury API, ThingMagic's universal programming interface, permits easy software portability across the entire ThingMagic product line – between finished readers and embedded modules.

Multiple Data Interfaces

Multipurpose client and host USB Ports, an SD card slot, and high voltage, opto-isolated general purpose I/O ports allow Sargas to support a wide variety of applications.



Left view



Right view



ThingMagic Sargas

Physical					
Dimensions (no connectors)		87 mm / 3.4 in. (L) x 80 mm / 3.1 in. (W) x 24 mm / 0.9 in. (H)			
Weight		0.27 kg / 0.6 lbs.			
Tag / Transponder Protocols					
RFID Protocol Support		EPCglobal Gen 2V2 (ISO 18000-63); ISO 18000-6B (optional) IP-X (optional, read-only); AEI ATA (optional, read-only)			
RF Interface					
Antenna Connectors		Two RP-SMA connectors			
RF Power Output		Read and write levels adjustable from 0 to +30 dBm			
Frequency Range Per Region		FCC 902-928 MHz (Americas), ETSI 865-868 MHz (EU), MCITT 865-867 MHz (India), MIC 916.8-920.8 MHz (Japan) <i>Customizable channel list permits subsets of these regions.</i>			
Data/Control Interface					
Control/Data Interfaces		RJ45 (10/100 Base-T Ethernet), USB Type B (client console, memory stick, and RNDIS port), USB Type A (accessory port), Micro SD			
GPIO Sensors and Indicators		8-Pin connector provides: 2 opto-isolated Inputs, 2 opto-isolated Outputs, 5V Source, Isolated and chassis grounds, DC input to set output levels			
User Indicators		Bi-color status LED, Power LED, 2 LAN LEDs			
Power					
Power Consumption	10W typical max, 15W worst case	External DC Power	5 VDC +/-5%	AC Adapter	100-240 VAC, 1A max, 50-60Hz
Regulatory Certifications & Environment					
Certifications		USA (FCC 47 Part 15); Canada (RSS-210); EU (ETSI EN 302 208 v3.1.1, RED 2014/53/EU), India (MCITT), Japan (MIC) and China (SRRC). FCC Class B for incidental emissions (EMI) <i>Other regional certifications may be available through reseller partners.</i>			
Safety & Other		ROHS compliant, IEC 60950-1 (ed. 2), CA-10430-UL			
Temperature		Operating -40°C to +60°C; Storage -40°C to +85°C			
Humidity		5%-95% non-condensing			
Performance					
Max Read Rate		>750 tags/second			
Max Tag Read Distance		>9 m (30 ft) with 9dBiC or 6dBiL antenna			
Application Interface					
Direct Communication		Low Level Reader Protocol (LLRP) v1.1 with multiprotocol and advanced extensions			
Host API		Mercury API: Java, C, C#.NET			
On-Reader API		Range of languages compiled with C/Java API			
Communication Channels		USB Keyboard emulator, Streaming to USB COM port, Network Telnet, Network HTTP Port			
Mercury OS Features					
Networking		DHCP and DNS-based configuration and firmware management, TCP/IP networking stack, Optional Wi-Fi support through external 3 rd party USB adapter			
Security		SSL/SSH-based security			
Web-based Control		Configuration, monitoring, and reading from web browser via HTTP (HTTPS future)			
Architecture					
O/S		Debian Linux kernel version 3.8			
Real-Time Clock		Backup time: 1 week at room temperatures			
Processor	1 GHz TI ARM Cortex-A8 (AM335x)	RAM	512 MB	Flash Memory	4 GB
Ordering Information					
Sargas Reader		S6-NA, S6-EU, S6-IN, S6-JP (high power)			
Power Adapter		PWRADP-S6-MR (Multi-Region)			
Development Kit		S6-DEVKIT (<i>does not include reader</i>)			
RAINstream License		TM-RAINSTM-LIC			
Protocol Licenses		(AEI ATA) S6-LIC-AEIATA, (IPX/ISO 18K-6B) S6-LIC-2F			

ABOUT JADAK:

JADAK, a business unit of Novanta, is a market leader in machine vision, RFID, barcode, printing, and color and light measurement products and services for original equipment manufacturers. The company designs and manufactures embedded detection and analysis solutions that help customers solve unique inspection, tracking, scanning and documenting challenges. The company is ISO 9001 and ISO 13485 registered.

Novanta is a trusted technology partner to OEMs in the medical and advanced industrial technology markets, with deep proprietary expertise in photonics, vision and precision motion technologies.

Novanta Rev 06062019

1 (888) 238-1155 Inside USA • 1 (205) 383-2244 Outside USA
info@atlasRFIDstore.com • www.atlasRFIDstore.com

atlasRFIDstore.com



JADAK
A Novanta Company

