

# UPS Battery Pack for SV-Series 3-Phase UPS, +/- 120VDC, 1 Cabinet - Tower, TAA, Batteries Included

MODEL NUMBER: **EBP240V2501**



External backup battery pack provides extended runtime for compatible Tripp Lite SV-Series 3-phase UPS systems.

## Features

**UPS Battery Pack Extends the Runtime of Your SV-Series 3-Phase UPS System** This external backup battery pack consists of one battery cabinet containing sealed lead acid batteries designed to give your SV-Series UPS system more runtime. It uses a +/-120VDC configuration and must be hardwired to a compatible UPS system. Multiple battery packs may be connected in parallel to increase runtime even longer. A UL-listed DC circuit breaker protects against too much current. The EBP240V2501 is compatible with all UPS models that begin with SV20, SV40, SV60, SV80, SV100, SV120 and SV140.

**Designed and Constructed to Ensure Consistent Power for a Long Time** This 120V UPS battery pack is made from heavy-gauge welded steel with a baked powder-coated finish that protects the cabinet from chipping and corrosion. The hinged cabinet door locks to prevent tampering and to facilitate easy access to the internal batteries. User-supplied power output cables feed into the cabinet through conduit knockouts built into the cabinet's exterior. Front and rear vents allow the free flow of warm air out of the cabinet to maintain cool internal temperatures. Sturdy metal casters allow you to smoothly roll the backup battery pack into position.

**TAA-Compliant for GSA Schedule Purchases** The EBP240V2501 is compliant with the Federal Trade Agreements Act (TAA), which makes it eligible for GSA (General Services Administration) Schedule and other federal procurement contracts.

## Specifications

OVERVIEW	
UPC Code	03733225283
INPUT	
Input Phase	3-Phase

## Highlights

- Extends runtime of SV-Series UPS systems using a +/- 120VDC configuration
- Sealed lead acid batteries offer safety, little maintenance and high power density
- Hardwired installation with circuit breakers providing overcurrent protection
- Multiple battery cabinets may be connected in parallel to increase runtime
- Complies with Federal Trade Agreements Act (TAA) for GSA Schedule purchases

## Applications

- Extend the runtime of your compatible Tripp Lite UPS system in a data center or telecom network
- Connect multiple battery packs in parallel to further extend runtime for mission-critical equipment

## System Requirements

- Any UPS model that begins with SV20, SV40, SV60, SV80, SV100, SV120 or SV140

## Package Includes

- EBP240V2501 UPS Battery Pack for SV-Series 3-Phase UPS w/Batteries, 1 Cabinet
- Owner's manual



Powering Business Worldwide



<b>BATTERY</b>	
Expandable Runtime	No
DC System Voltage (VDC)	+/- 120VDC
UPS Connection	Hardwire (contractor supplies wiring - see Owner's Manual for requirements and installation information)
<b>PHYSICAL</b>	
Material of Construction	Steel
External Battery Pack Form Factor	Tower
Installation Form Factors Supported with Included Accessories	Tower
Shipping Dimensions (hwd / in.)	64.50 x 29.00 x 31.50
Shipping Weight (lbs.)	1673.00
Shipping Weight (kg)	758.86
Unit Dimensions (hwd / in.)	59.000 x 29.000 x 31.500
Unit Dimensions (hwd / cm)	149.86 x 73.66 x 80.01
Unit Weight (lbs.)	1593
Unit Weight (kg)	722.57
<b>STANDARDS &amp; COMPLIANCE</b>	
Product Certifications	EN 60950-1; CSA (Canada); CAN/CSA-C22.2 No. 107.1 (Canada); IEC/EN 62040; UL 1778
Product Compliance	RoHS; UKCA; Trade Agreements Act (TAA)
<b>WARRANTY &amp; SUPPORT</b>	
Product Warranty Period (Worldwide)	1-year limited warranty

1000 Eaton Boulevard  
 Cleveland, OH 44122  
 United States  
<https://tripplite.eaton.com>

© 2026 Eaton. All Rights Reserved.  
 Eaton is a registered trademark. All other trademarks  
 are the property of their respective owners.